



AC FLEXIBLE CURRENT SENSOR CT9667

Clamp sensor



Introducing 2 new variations with a thinner cable!



**Easy to loop
around, even in
confined spaces**



Use with a power quality analyzer or power meter

Thinner cable type is easy to use in confined spaces and with complex wiring

Thin cable type

New CT9667-01


Measurable conductor diameter
 $\phi 100$ mm (3.94")
 Cable diameter
 $\phi 7.5$ mm (0.30")



In confined spaces

New CT9667-02

Measurable conductor diameter
 $\phi 180$ mm (7.09")
 Cable diameter
 $\phi 7.5$ mm (0.30")



Shaped so that it's easy to route through complex wiring

Large-diameter type
 CT9667-03

Measurable conductor diameter
 $\phi 254$ mm (10.00")
 Cable diameter
 $\phi 13$ mm (0.51")



For large-diameter applications such as busbars

Designed for use with power quality analyzers and clamp-on power meters

Use with the following products.

Power quality analyzers



PW3198



3197

Clamp-on power meters



PW3360



PW3365



3169

Product specifications

(Accuracy guaranteed for 1 year, Post-adjustment accuracy guaranteed for 1 year)

Model	CT9667-01	CT9667-02	CT9667-03
Measurable conductor diameter	$\phi 100$ mm (3.94")	$\phi 180$ mm (7.09")	$\phi 254$ mm (10.00")
Rated input current	5000 A AC/ 500 A AC		
Maximum allowable input	Continuous 10000 A (at 45 to 66 Hz, requires derating at frequency)		
Operating temperature range	-10 to 60°C (14 to 140°F)		0 to 50°C (32 to 122°F)
Dust and water resistance	Sensor only IP50 (EN 60529:1991 + A1:2000)		-
Output voltage	5000 A range: 500 mV/f.s. AC (0.1 mV/A AC) 500 A range: 500 mV/f.s. AC (1 mV/A AC)		
Amplitude accuracy	$\pm 2\%$ rdg. $\pm 0.3\%$ f.s. (45 to 66 Hz, with conductor positioned at center of loop)		
Phase accuracy	Within $\pm 1^\circ$ (45 to 66 Hz)		
Frequency bandwidth	10 Hz to 20 kHz (within ± 3 dB)		
Maximum rated voltage to earth	1000 V AC (measurement category III), 600 V AC (measurement category IV)		
Power supply	LR6 (AA) alkaline batteries x2; continuous operating time: 7 days; rated output: 35 mVA AC ADAPTER 9445-02 (Universal 100 to 240VAC, 9V/1A output/for UL type); rated output: 0.2 VA AC ADAPTER 9445-03 (universal 100 to 240VAC, 9V/1A output/for EU type); rated output: 0.2 VA External DC power supply (5 to 15 V DC); rated output: 0.2 VA		
Dimensions	Loop cable diameter: $\phi 7.5$ mm (0.30")		Loop cable diameter: $\phi 13$ mm (0.51")
	Cable length: Between sensor and battery box: 2 m (6.56 ft). Output cable: 1 m (3.28 ft) Battery box: 35 mm (1.38 in)W x 120.5 mm (4.74 in)H x 34 mm (1.34 in)D		
Mass (Including batteries)	280 g (9.9 oz)		470 g (16.6 oz)
Accessories	LR6 (AA) alkaline batteries x2, Instruction manual x1		



Connection lock mechanism



Range switch


Options



AC ADAPTER 9445-02
 (universal 100 to 240VAC,
 9V/1A output/for UL type)



AC ADAPTER 9445-03
 (universal 100 to 240VAC,
 9V/1A output/for EU type)



Loop (sensor portion)

Note: Company names and Product names appearing in this catalog are trademarks or registered trademarks of various companies.

HIOKI

HIOKI E. E. CORPORATION

HEADQUARTERS

81 Koizumi, Ueda, Nagano, 386-1192, Japan
 TEL +81-268-28-0562 FAX +81-268-28-0568
<http://www.hioki.com/> / E-mail: os-com@hioki.co.jp

HIOKI USA CORPORATION

TEL +1-609-409-9109 FAX +1-609-409-9108
<http://www.hioki.com/> / E-mail: hioki@hioki.com

HIOKI (Shanghai) SALES & TRADING CO., LTD.
 TEL +86-21-63910090 FAX +86-21-63910360
<http://www.hioki.cn/> / E-mail: info@hioki.com.cn

HIOKI INDIA PRIVATE LIMITED
 TEL +91-124-6590210 FAX +91-124-6460113
 E-mail: hioki@hioki.in

HIOKI SINGAPORE PTE. LTD.
 TEL +65-6634-7677 FAX +65-6634-7477
 E-mail: info-sg@hioki.com.sg

HIOKI KOREA CO., LTD.
 TEL +82-2-2183-8847 FAX +82-2-2183-3360
 E-mail: info-kr@hioki.co.jp

DISTRIBUTED BY